

Optimized Signal Channel Count for Slip Rings Using Spinning Amplifiers

10 Channel Slip Ring Assembly*

	350 OHM BRIDGE		120 OHM BRIDGE		THERMOCOUPLES
	5 VDC EXCITATION	10 VDC EXCITATION	5 VDC EXCITATION	10 VDC EXCITATION	N/A
+ 15 V	1	1	1	1	1
- 15 V	1	1	1	1	1
Power Common	1	1	1	1	1
Calibration Control	1	1	1	1	N/A
Signal Common	1	1	1	1	1
Signal Channels	5	5	5	5	6
Current in Each Power Ring (mA)	.150	225	300	500	100

20 Channel Slip Ring Assembly*

	350 OHM BRIDGE		120 OHM BRIDGE		THERMOCOUPLES
	5 VDC EXCITATION	10 VDC EXCITATION	5 VDC EXCITATION	10 VDC EXCITATION	N/A
+ 15 V	1	1	1	1	1
- 15 V	1	1	1	1	1
Power Common	1	1	1	1	1
Calibration Control	1	1	1	1	N/A
Signal Common	1	1	1	1	1
Signal Channels	15	15	15	15	17
Current in Each Power Ring (mA)	.150	225	300	500	100

36 Channel Slip Ring Assembly*

	350 OHM BRIDGE		120 OHM BRIDGE		THERMOCOUPLES
	5 VDC EXCITATION	10 VDC EXCITATION	5 VDC EXCITATION	10 VDC EXCITATION	N/A
+ 15 V	1	2	2	3	1
- 15 V	1	2	2	3	1
Power Common	1	1	1	1	1
Calibration Control	1	1	1	1	N/A
Signal Common	1	1	1	1	1
Signal Channels	31**	29**	29**	27**	32
Current in Each Power Ring (mA)	930	650	840	900	480

* Slip Ring assembly limit: 1 Amp per circuit connection

** Requires more than one Amplifier Control Unit (PS-DC).

8500 Ance Road
 Charlevoix, MI 49720
 Tel: 231-547-5511
 Fax: 231-547-7070
 Rev: 8/16/06

MICHIGAN SCIENTIFIC
<http://www.michsci.com>
 Email: mscinfo@michsci.com
 corporation

321 East Huron Street
 Milford, MI 48381
 Tel: 248-685-3939
 Fax: 248-684-5406

This page is intentionally blank.